





Quiescent current	0mA (none).
Alarm current	Determined by the number/type of field devices connected to the call controller/system.
Auxiliary relays	2 volt free relay contacts (NO/C/NC). Activate when a standard or emergency call is received by the controller. Both relays rated at 30V d.c. @ 1A.
Auxiliary inputs	External PSU Input: 9V-15V d.c. @ 400mA (suitable for use with an BF560-12 12V 2A boxed PSU which has space available for a 12V 7AH battery).
Indicators	Green Power on LED; 10 x red Zonal Alarm LEDs (lit steady for a Standard call, pulse for an Emergency call); Internal buzzer (on steady for any Standard call, intermittent for any Emergency call).
Controls	2 Buttons - (A) Reset or inactive ; (B) 'Mute' or 'Call Accept'. (Both buttons are link selectable). If Call Accept is selected indicators on relevant field devices will emit a slow intermittent to
Expansion connections	CONN2 allows the connection of 1 x NC910EF 10 Zone Expansion Unit or 1x NC920EF 20 Zone Expansion Unit.
Call acknowledgement functionality	Yes.
Product dimensions (mm)	214 W x 178 H x 70 D mm. Surface mounting.
Construction & finish	Plastic detachable lid and back box. RAL7035.
IP Rating	IP41.
Weight	1.27kg.
Operating conditions/temperature	-5°C to +40°C. Max. relative humidity 95% non-condensing.



T 01942 322744 E sales@c-tec.co.uk  
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom