

Quantec Addressable Call Point, Button Reset (No Remote)

Part No. **QT609**



Overview

- A programmable Quantec addressable call point.
- Includes a Call button, Reset button and red/green confidence light.
- Can make up to 5 levels of call - Standard, Ensuite, Help Required, Emergency, Presence & Attendance (dependent on configuration and ancillary devices used). Attack and Attendance calls can also be made if connected to compatible slave infrared receiver.
- Can be programmed to operate in a multitude of ways using a QT423 configurator.
- Connections provided for additional slave devices such as ceiling pulls, overdoor lights, slave infrared receivers and more.
- QT609M magnetic reset version also available.

More Information

Technical Specifications

Power requirements	Nominal 24V DC (from Quantec Controller/Network)
Quiescent current	Less than 3mA.
Alarm current	14mA.
Indicators	Red/green confidence LED.
Controls	Call button; Reset button. (QT609M magnetic reset version also available).
Connections	Net +; Net -; R; G; L+; SW; IR; SLV.
Expansion connections	R; G; L+; SW; IR & SLV terminals allow the connection of optional slave overdoor lights, slave call points, slave ceiling pulls and slave infrared receivers.
Onboard 6.35mm Remote Jack Socket No.	



Onboard Sounder	No,
Onboard Infrared Receiver	No.
Product dimensions (mm)	86 W x 86 H x 23 D mm. Can be mounted on a standard UK 25mm single gang flush or surface back box.
Construction & finish	Plastic.
IP Rating	IP41.
Weight	32g.
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom